

Vecta₂[™] Direction Finder

Product No. 2769.4



- > "Alert and Locate" system allows user to monitor 121.5 MHz frequency for use in emergency locating situations
- > Innovative Macro/Zoom dual scale displays 255 units of signal strength and provides ultra sensitive interpretation of signal direction
- > Rugged, stainless steel body design with collapsible PCB antennas
- > Channel 2 training frequency of 121.775

- > Mini-yagi antenna design provides decisive directional signal indication
- > Weather resistant; can be used in light rain and damp conditions
- > Speaker with volume control amplifies audible tone of beacon
- > -113dbm sensitive receiver detects weak signals at maximum range
- > User friendly display with large touch pad controls

Size: 9.0 x 2.5 x 1.5 in (23 x 6 x 4 cm)
9.0 x 16.0 x 1.5 in (23 x 40.6 x 4 cm) with antenna opened

Weight: 15.6 oz (442 g) with battery and handle

- Material:** Aluminum body, PCB antennas
- Color:** Stainless Steel with blue label
- Application:** Offshore racing and cruising, dive boats, crew-overboard situations; all SAR responsible for PLB searches
- Waterproof:** Weather resistant; can be used in light rain and damp conditions
- Accessories:** Carry Case, hip pouch, AC/DC power supply, fold down handle, headphones, remote antenna, training video, 3-ft (91 cm) low profile whip antenna
- Operating Life:** 30 hours continuous on one battery, unlimited operating life on either AC or DC power supply
- Battery Type:** 2-2/3 A Lithium (DL223A Duracell), common camera battery, readily available
- Carton Dimensions:** 12.0 x 14.0 x 6.0 in (31.0 x 35.6 x 15.0 cm)
- Units Per Carton:** 1
- Limited Warranty:** 1 year



Complete Case



Vecta₂[™] Mounted w/closed antennas



ACR Electronics, Inc.
5757 Ravenswood Road
Fort Lauderdale, FL 33312, U.S.A.
Tel Worldwide: +1(954) 981-3333
Fax: +1(954) 983-5087
www.acrelectronics.com